


NASA TECH BRIEF



NASA Tech Briefs announce new technology derived from the U.S. space program. They are issued to encourage commercial application. Tech Briefs are available on a subscription basis from the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia 22151. Requests for individual copies or questions relating to the Tech Brief program may be directed to the Technology Utilization Division, NASA, Code UT, Washington, D.C. 20546.

Block Encoders for Reed-Muller Codes



Block Diagram Logic Circuit
for Reed-Muller Code Scheme.

The problem:

To increase error-free reception by a high-rate telemetry channel under extremely adverse signal-noise with minimal use of additional hardware. The format of the transmitted data is a block-encoded, 6-bit orthogonal code-word.

The solution:

Encoding algorithms were developed for generating a 32×64 -bit matrix Reed-Muller code from the 6-bit orthogonal code; the larger matrix increases the probability of error-free reception. Variations of logic circuits were designed to implement the block encoding schemes.

How it's done:

The Reed-Muller code is constructed as follows:

$$A = \begin{bmatrix} +1 & +1 \\ +1 & -1 \end{bmatrix}; \quad B = \begin{bmatrix} A & A \\ A & \bar{A} \end{bmatrix}; \quad N = \begin{bmatrix} (N-1) & (N-1) \\ (N-1) & \overline{(N-1)} \end{bmatrix}$$

An orthogonal matrix of a simple two-variable code

dictionary is formed by adding the complement of the code in the lower right, i. e.,

1	1	1	1
1	-1	1	-1
1	1	-1	-1
1	-1	-1	1

Two-variable

From the Reed-Muller code structure it may be deduced that each code symbol is a mod-2 function between a certain set of the original information bits; the selection of these sets of the original information bits is a simple mapping between the original information bits and the binary sequence. In the application, the mod-2 function is equivalent to a parity function which indicates whether the number of "ones" in a vector (i.e., in a row or column of the matrix) is odd or even.

The criteria for the design of a logic circuit which implements the code scheme, shown in the figure, are based on the mod-2 algebraic expressions:

(continued overleaf)

$$X \oplus 0 = X$$

$$X \oplus X = 0$$

$$X \oplus X \oplus X = X$$

$$X \oplus X \oplus X \oplus X = 0, \text{ etc.}$$

Odd number of X equals X, even number X equals 0.

If a set of variables in the shift register is continually shifted around and entered through the mod-2 function between the output register and another variable (every other cycle), and each variable in the register will be mod-2 added with the entry variable and every other time not. A mod-2 mapping between the entry variables and the binary sequence is obtained by several modules connected together by two-term mod-2 functions. For a large number of variables, identical modules can be added as required and each new module is clocked once every other cycle of the preceding one.

Note:

Requests for further information may be directed to:

Technology Utilization Officer

NASA Pasadena Office

4800 Oak Grove Drive

Pasadena, California 91103

Reference: B 70-10051

Patent status:

This invention is owned by NASA, and a patent application has been filed. Royalty-free, nonexclusive licenses for its commercial use will be granted by NASA. Inquiries concerning license rights should be made to NASA, Code GP, Washington, D.C. 20546.

Source: Tage O. Anderson of
Caltech/JPL

under contract to
NASA Pasadena Office
(NPO-10629 and
NPO-10636)